

# DMP KEYPAD QUICKGUIDE



DMP 7060

**Arm System** – All protected windows and doors must be closed. Ready light should be green. Screen should say “SYSTEM READY”

- **ALL**— Press and hold “**ALL**” Button (# 1) or Press **Code** then “1” key. Arms all devices including motion detectors.
- **Perimeter**— Press and Hold “**PERIM**” Button (#6) or Press **Code** then “6” key. Arms all devices and automatically bypass all motion detectors.
- **Instant**— Press and hold “**PERIM**” (#6) Key. After few seconds “**INST**” appears on top right hand side of screen. Press SELECT button below “**INST**” button. Arms entry doors without delay and bypass all motion detectors.

**Turn System Off/Silence an Alarm:** Enter user **CODE** then “**CMD**” key OR Press “**CMD**” key, Press button below “**DISARM**”, Enter CODE, Press “**CMD**” key.

**Reset System:** Press and Hold “**RESET**” (#2) Button.

**Display Faulted Zones:** When screen reads “**NOT READY**”, press top right button. Screen MUST SAY “**NOT READY**” to display faulted zones.

**Door Chime On/Off:** Press and hold “**CHIME**” (#5) button. Then press “**CMD**” key until “**MENU**” appears. Press selection key under “**MENU**” (YES). Press “**CMD**” until CHIME appears on the screen. Press any top selection button to toggle off/on.

**Bypass a Zone:** If zone is already faulted (ex: Door/Window is open), arm system in desired mode (ALL, PERIMETER). “**OKAY BYPASS STOP**” Appears on screen. Press either button below “**BYPASS**” to bypass faulted zone.

IF ZONE IS NOT FAULTED, press “**CMD**” until “**MENU**” appears. Press selection key (YES) underneath “**MENU**”. Press “**CMD**” until “**BYPASS**” appears. Press any top selection button. Enter Zone number (1, 2, 3 etc..) and then button under “**BYPASS**”

**Panic Buttons:** **MEDICAL:** Simultaneously press top left 2 buttons above green “!”.  
**POLICE:** Simultaneously press top middle 2 buttons above blue shield.  
**FIRE:** Simultaneously press top right 2 buttons above red flame.

**Change or Add Additional Codes:** EMAIL [codechange@iAlarmNJ.com](mailto:codechange@iAlarmNJ.com) with changes.

**Delete A User Code:** EMAIL [codechange@iAlarmNJ.com](mailto:codechange@iAlarmNJ.com) with changes.

**Sending a Test Signal:** Press “**CMD**” key until “**MENU**” appears. Press select button under “**YES**”. Press “**CMD**” key again until “**SYSTEM TEST**” appears. Press any top button.



CLOSE UP-DMP 1-6 KEYS



DMP COMMAND (CMD) KEY



MEDICAL POLICE FIRE

DMP SCREEN & SELECT/PANIC KEYS



DMP DIGIT KEYS CLOSE UP